

MARINE AMPLIFIER



BIG POWER



www.BAZOOKA.com
For more information in USA:
Southern Audio Services, Inc.
14763 Florida Blvd.
Baton Rouge, LA 70819
1-800-THE-TUBE

SMALL DEVICE INCLUDES BASS REMOTE CONTROL

- Class D digital amplifier technology
- Low current draw
- Small footprint design



MARINE AMPLIFIER *Bazooka*



model # MA1600D
1 CHANNEL

RMS Power @ 14.4 V DC	
Power @ 4 Ohms	320WX1
Power @ 2 Ohms	600WX1
Min. Speaker Impedance	20HM
THD Distortion	0.1%
Frequency Response	20Hz~20KHz
Input Sensitivity	0.2V~6V
Input Impedance	10K
Signal-to-Noise Ratio	90 dB

Channel Separation	55 dB
Remote gain control	0.2V~+6V
Crossover Network	
Phase Control	0~180°C
Low Pass Filter	30Hz~1KHz
Bass Boost	0dB~+18dB
Subsonic Filter	10Hz~+45Hz
Fuse Rating	40Ax1
Size L x W x H	9.25" x 5.5" x 1.75"



model # MA275D
2 CHANNEL

RMS Power @ 14.4 V DC	
Power @ 4 Ohms	70WX2
Power @ 2 Ohms	100WX2
Bridged Power @ 4 Ohms	170WX1
Min. Speaker Impedance	20HM
THD Distortion	0.1%
Frequency Response	20Hz~20KHz
Input Sensitivity	0.2V~6V
Input Impedance	10K
Signal-to-Noise Ratio	90 dB

Channel Separation	55 dB
Remote gain control	0.2V~+6V
Crossover Network	
Low Pass Filter	50Hz~500Hz
High Pass Filter	50Hz~500Hz
Bass Boost	0dB~+12dB
Treble Boost	0dB~+12dB
Fuse Rating	20Ax1
Size L x W x H	9.25" x 5.5" x 1.75"



model # MA475D
4 CHANNEL

RMS Power @ 14.4 V DC	
Power @ 4 Ohms	80WX4
Power @ 2 Ohms	100WX4
Bridged Power @ 4 Ohms	170WX2
Min. Speaker Impedance	20HM
THD Distortion	0.1%
Frequency Response	20Hz~20KHz
Input Sensitivity	0.2V~6V
Input Impedance	10K
Signal-to-Noise Ratio	90 dB

Channel Separation	55 dB
Remote gain control	0.2V~+6V
Crossover Network	
Low Pass Filter	50Hz~500Hz
High Pass Filter	50Hz~500Hz
Bass Boost	0dB~+12dB
Treble Boost	0dB~+12dB
Fuse Rating	40Ax1
Size L x W x H	9.25" x 5.5" x 1.75"